

NAG Toolbox

nag_sum_convcorr_complex (c06pk)

1 Purpose

nag_sum_convcorr_complex (c06pk) calculates the circular convolution or correlation of two complex vectors of period n .

2 Syntax

```
[x, y, ifail] = nag_sum_convcorr_complex(job, x, y, 'n', n)
```

```
[x, y, ifail] = c06pk(job, x, y, 'n', n)
```

3 Description

nag_sum_convcorr_complex (c06pk) computes:

if **job** = 1, the discrete **convolution** of x and y , defined by

$$z_k = \sum_{j=0}^{n-1} x_j y_{k-j} = \sum_{j=0}^{n-1} x_{k-j} y_j;$$

if **job** = 2, the discrete **correlation** of x and y defined by

$$w_k = \sum_{j=0}^{n-1} \bar{x}_j y_{k+j}.$$

Here x and y are complex vectors, assumed to be periodic, with period n , i.e., $x_j = x_{j\pm n} = x_{j\pm 2n} = \dots$; z and w are then also periodic with period n .

Note: this usage of the terms ‘convolution’ and ‘correlation’ is taken from Brigham (1974). The term ‘convolution’ is sometimes used to denote both these computations.

If \hat{x} , \hat{y} , \hat{z} and \hat{w} are the discrete Fourier transforms of these sequences, and \tilde{x} is the inverse discrete Fourier transform of the sequence x_j , i.e.,

$$\hat{x}_k = \frac{1}{\sqrt{n}} \sum_{j=0}^{n-1} x_j \times \exp\left(-i \frac{2\pi jk}{n}\right), \text{ etc.},$$

and

$$\tilde{x}_k = \frac{1}{\sqrt{n}} \sum_{j=0}^{n-1} x_j \times \exp\left(i \frac{2\pi jk}{n}\right),$$

then $\hat{z}_k = \sqrt{n} \cdot \hat{x}_k \hat{y}_k$ and $\hat{w}_k = \sqrt{n} \cdot \tilde{x}_k \hat{y}_k$ (the bar denoting complex conjugate).

4 References

Brigham E O (1974) *The Fast Fourier Transform* Prentice–Hall

5 Parameters

5.1 Compulsory Input Parameters

1: **job** – INTEGER

The computation to be performed:

job = 1

$$z_k = \sum_{j=0}^{n-1} x_j y_{k-j} \text{ (convolution);}$$

job = 2

$$w_k = \sum_{j=0}^{n-1} \bar{x}_j y_{k+j} \text{ (correlation).}$$

Constraint: **job** = 1 or 2.

2: **x(n)** – COMPLEX (KIND=nag_wp) array

The elements of one period of the vector x . If **x** is declared with bounds $(0 : n - 1)$ in the function from which nag_sum_convcorr_complex (c06pk) is called, then **x(j)** must contain x_j , for $j = 0, 1, \dots, n - 1$.

3: **y(n)** – COMPLEX (KIND=nag_wp) array

The elements of one period of the vector y . If **y** is declared with bounds $(0 : n - 1)$ in the function from which nag_sum_convcorr_complex (c06pk) is called, then **y(j)** must contain y_j , for $j = 0, 1, \dots, n - 1$.

5.2 Optional Input Parameters

1: **n** – INTEGER

Default: the dimension of the arrays **x**, **y**. (An error is raised if these dimensions are not equal.)
 n , the number of values in one period of the vectors **x** and **y**. The total number of prime factors of **n**, counting repetitions, must not exceed 30.

Constraint: **n** \geq 1.

5.3 Output Parameters

1: **x(n)** – COMPLEX (KIND=nag_wp) array

The corresponding elements of the discrete convolution or correlation.

2: **y(n)** – COMPLEX (KIND=nag_wp) array

The discrete Fourier transform of the convolution or correlation returned in the array **x**.

3: **ifail** – INTEGER

ifail = 0 unless the function detects an error (see Section 5).

6 Error Indicators and Warnings

Errors or warnings detected by the function:

ifail = 1

On entry, **n** < 1.

ifail = 2

On entry, **job** \neq 1 or 2.

ifail = 3

An unexpected error has occurred in an internal call. Check all function calls and array dimensions. Seek expert help.

ifail = 4

On entry, **n** has more than 30 prime factors.

ifail = -99

An unexpected error has been triggered by this routine. Please contact NAG.

ifail = -399

Your licence key may have expired or may not have been installed correctly.

ifail = -999

Dynamic memory allocation failed.

7 Accuracy

The results should be accurate to within a small multiple of the *machine precision*.

8 Further Comments

The time taken is approximately proportional to $n \times \log(n)$, but also depends on the factorization of n . `nag_sum_convcorr_complex (c06pk)` is faster if the only prime factors of n are 2, 3 or 5; and fastest of all if n is a power of 2.

9 Example

This example reads in the elements of one period of two complex vectors x and y , and prints their discrete convolution and correlation (as computed by `nag_sum_convcorr_complex (c06pk)`). In realistic computations the number of data values would be much larger.

9.1 Program Text

```
function c06pk_example
    fprintf('c06pk example results\n\n');

    a = 1 - 0.5i;
    b = - 0.5i;
    x(1:5) = a;
    x(6:9) = b;
    y(1:4) = a/2;
    y(5:9) = b/2;

    job = nag_int(1);
    [conv, tconv, ifail] = c06pk(job, x, y);
    job = nag_int(2);
    [corr, tcorr, ifail] = c06pk(job, x, y);

    result = [transpose(conv) transpose(corr)];
    disp('      Convolution      Correlation');
    disp(result);
```

9.2 Program Results

c06pk example results

Convolution	Correlation
-0.6250 - 2.2500i	3.1250 - 0.2500i
-0.1250 - 2.2500i	2.6250 - 0.2500i
0.3750 - 2.2500i	2.1250 - 0.2500i
0.8750 - 2.2500i	1.6250 - 0.2500i
0.8750 - 2.2500i	1.1250 - 0.2500i
0.3750 - 2.2500i	1.6250 - 0.2500i
-0.1250 - 2.2500i	2.1250 - 0.2500i
-0.6250 - 2.2500i	2.6250 - 0.2500i
-1.1250 - 2.2500i	3.1250 - 0.2500i
