

NAG Toolbox

nag_sum_fft_real_2d (c06pv)

1 Purpose

nag_sum_fft_real_2d (c06pv) computes the two-dimensional discrete Fourier transform of a bivariate sequence of real data values.

2 Syntax

```
[y, ifail] = nag_sum_fft_real_2d(m, n, x)
```

```
[y, ifail] = c06pv(m, n, x)
```

3 Description

nag_sum_fft_real_2d (c06pv) computes the two-dimensional discrete Fourier transform of a bivariate sequence of real data values $x_{j_1 j_2}$, for $j_1 = 0, 1, \dots, m - 1$ and $j_2 = 0, 1, \dots, n - 1$.

The discrete Fourier transform is here defined by

$$\hat{z}_{k_1 k_2} = \frac{1}{\sqrt{mn}} \sum_{j_1=0}^{m-1} \sum_{j_2=0}^{n-1} x_{j_1 j_2} \times \exp\left(-2\pi i \left(\frac{j_1 k_1}{m} + \frac{j_2 k_2}{n}\right)\right),$$

where $k_1 = 0, 1, \dots, m - 1$ and $k_2 = 0, 1, \dots, n - 1$. (Note the scale factor of $\frac{1}{\sqrt{mn}}$ in this definition.)

The transformed values $\hat{z}_{k_1 k_2}$ are complex. Because of conjugate symmetry (i.e., $\hat{z}_{k_1 k_2}$ is the complex conjugate of $\hat{z}_{(m-k_1)k_2}$), only slightly more than half of the Fourier coefficients need to be stored in the output.

A call of nag_sum_fft_real_2d (c06pv) followed by a call of nag_sum_fft_hermitian_2d (c06pw) will restore the original data.

This function calls nag_sum_fft_realherm_1d_multi_col (c06pq) and nag_sum_fft_complex_1d_multi_row (c06pr) to perform multiple one-dimensional discrete Fourier transforms by the fast Fourier transform (FFT) algorithm in Brigham (1974) and Temperton (1983).

4 References

Brigham E O (1974) *The Fast Fourier Transform* Prentice–Hall

Temperton C (1983) Fast mixed-radix real Fourier transforms *J. Comput. Phys.* **52** 340–350

5 Parameters

5.1 Compulsory Input Parameters

1: **m** – INTEGER

m , the first dimension of the transform.

Constraint: $m \geq 1$.

2: **n** – INTEGER

n , the second dimension of the transform.

Constraint: $n \geq 1$.

3: $\mathbf{x}(\mathbf{m} \times \mathbf{n})$ – REAL (KIND=nag_wp) array

The real input dataset x , where $x_{j_1 j_2}$ is stored in $\mathbf{x}(j_2 \times m + j_1)$, for $j_1 = 0, 1, \dots, m - 1$ and $j_2 = 0, 1, \dots, n - 1$. That is, if \mathbf{x} is regarded as a two-dimensional array of dimension $(0 : \mathbf{m} - 1, 0 : \mathbf{n} - 1)$, then $\mathbf{x}(j_1, j_2)$ must contain $x_{j_1 j_2}$.

5.2 Optional Input Parameters

None.

5.3 Output Parameters

1: $\mathbf{y}((\mathbf{m}/2 + 1) \times \mathbf{n})$ – COMPLEX (KIND=nag_wp) array

The complex output dataset \hat{z} , where $\hat{z}_{k_1 k_2}$ is stored in $\mathbf{y}(k_2 \times (m/2 + 1) + k_1)$, for $k_1 = 0, 1, \dots, m/2$ and $k_2 = 0, 1, \dots, n - 1$. That is, if \mathbf{y} is regarded as a two-dimensional array of dimension $(0 : \mathbf{m}/2, 0 : \mathbf{n} - 1)$, then $\mathbf{y}(k_1, k_2)$ contains $\hat{z}_{k_1 k_2}$. Note the first dimension is cut roughly by half to remove the redundant information due to conjugate symmetry.

2: **ifail** – INTEGER

ifail = 0 unless the function detects an error (see Section 5).

6 Error Indicators and Warnings

Errors or warnings detected by the function:

ifail = 1

Constraint: $\mathbf{m} \geq 1$.

ifail = 2

Constraint: $\mathbf{n} \geq 1$.

ifail = 3

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please contact NAG for assistance.

ifail = -99

An unexpected error has been triggered by this routine. Please contact NAG.

ifail = -399

Your licence key may have expired or may not have been installed correctly.

ifail = -999

Dynamic memory allocation failed.

7 Accuracy

Some indication of accuracy can be obtained by performing a forward transform using `nag_sum_fft_real_2d` (c06pv) and a backward transform using `nag_sum_fft_hermitian_2d` (c06pw), and comparing the results with the original sequence (in exact arithmetic they would be identical).

8 Further Comments

The time taken by `nag_sum_fft_real_2d` (c06pv) is approximately proportional to $m \log(mn)$, but also depends on the factors of m and n . `nag_sum_fft_real_2d` (c06pv) is fastest if the only prime factors of m and n are 2, 3 and 5, and is particularly slow if m or n is a large prime, or has large prime factors.

Workspace is internally allocated by `nag_sum_fft_real_2d` (c06pv). The total size of these arrays is approximately proportional to mn .

9 Example

This example reads in a bivariate sequence of real data values and prints their discrete Fourier transforms as computed by `nag_sum_fft_real_2d` (c06pv). Inverse transforms are then calculated by calling `nag_sum_fft_hermitian_2d` (c06pw) showing that the original sequences are restored.

9.1 Program Text

```
function c06pv_example
fprintf('c06pv example results\n\n');

m = nag_int(5);
n = nag_int(2);
x = [0.010  0.346;
     1.284  1.960;
     1.754  0.855;
     0.089  0.161;
     1.004  1.844];

% Compute Transform
[y, ifail] = c06pv(m, n, x);
fprintf('\nComponents of discrete Fourier transform\n');
% Display as 2-d array
disp(reshape(y, m/2, n));

% Compute Inverse Transform
[x, ifail] = c06pw(m, n, y);
fprintf('Original sequence as restored by inverse transform\n');
% Display as 2-d array
disp(reshape(x, m, n));
```

9.2 Program Results

```
c06pv example results

Components of discrete Fourier transform
 2.9431 + 0.0000i  -0.3241 + 0.0000i
-0.0235 - 0.5576i  -0.4660 - 0.2298i
-1.1666 + 0.6359i   0.3624 + 0.2615i

Original sequence as restored by inverse transform
 0.0100  0.3460
 1.2840  1.9600
 1.7540  0.8550
 0.0890  0.1610
 1.0040  1.8440
```
